

128k (1MBit) Memory Configurations. V4.5 to V5.1

(Also applicable to V3.5 & V4 with the exceptions shown in brackets)

V3 / V4 / V4.5 / V5 / V5.1 128k (1MBit)	Standard	Access	Enlarged	Apartments V4.5 or later	Access 2 V4.5 or later	Special	Alarms
Users	2000	1000	1000	500	1000	1000	1000
User Names	100	1000	100	500	1000	1000	200
User RF Fobs ‡	25	25	0	25	25	25	25
User Types	32	64	32	64	64	64	48
Card Only Users *	0	0	0	0	0	0	0
Areas	96	32	96	48	32	32	64 (96)
Doors	32	64	16	48	64	48 (64)	16
Lift Cars *	3	6	3	4	6	4	3
Site Codes	6	5	6	6	5	6	5
TimeZones	32	32	32	32	32	32	32
Holidays	16	16	16	16	16	16	16
Diaries	10	10	10	10	10	10	10
Review Memory	2000	2000	2000	2000	2000	2000	2000
Counters	8	8	16	4	4	8	8
Area Lists	96	32	96	48	32	32	64 (96)
Doors Lists	48	64	32	48	64	48 (64)	32
Siren Lists	32	16	32	16	16	8 (16)	32
Floor Lists *	24	48	24	32	32	32 (48)	24
Lift Car Lists *	6	12	6	6	6	8	6
Auxiliary Lists	32	32	32	16	32	32	32
Menu Groups	16 (8)	8	16	8	8	8	16
Access Groups	16	12 (16)	16	12	16	16	8
Process Groups	32	24 (32)	32	32	32	32	32
Interlock Groups *	16	32	12	8	16	16 (32)	8
Comms Tasks	6	6	6	6	6	6	8
Phone Numbers	8	8	8	12	12	8	12
DTMF Controls	16	16	16	8	8	16	16
Function Zones	32	16	32	32	16	16	32
Calculated Auxes	32	16	32	32	16	16	32
Home Auxiliaries	64	32	64	32	32	32	32
Home Zones	32	16	64	16	16	16	64
Automation Auxiliaries ^	16 (0)	16 (0)	16 (0)	16 (0)	16 (0)	16 (0)	16 (0)
LCD Terminals	32	16	32	32	16	16	32
Expander Modules 32Z	4	2	6	2	2	1	15
Expander Modules 16Z	6	6	8	8	4	2	0
Reader Modules	16	32	8	32	32	8	8
Mini Expander Modules	5	4	10	5	4	16	4
Analogue Modules	2	4	4	2	2	4	4
Intelligent 4Dr Access Modules	0	0	2 (0)	4	0	8	2
LAN Pwr Supply Modules	2 (0)	2 (0)	2 (0)	6 (0)	6 (0)	2 (0)	2 (0)
Wireless Network Modules	2	0 (2)	6 (8) †	0 (2)	0 (2)	0 (2)	0 (4)
RF Expander Modules ‡	2	1	0	2	2	2	2
AirCon Control *	2	2 (4)	2 (4)	2	2	2 (4)	2 (4)

- NOTES:
- 1) Only Users with names have Expiry dates in the 128k Memory configurations.
 - 2) * Only available in Access 4000.
 - 3) () Changes from V3.5 / V4. Where values differ from V3.5/V4, the old values are shown in brackets.
 - 4) ^ “Automation I/F Auxiliaries” were formerly called “C-Bus Auxiliaries”.
 - 5) † Requires Options Micro Chip upgrade to support more than 32 Inovonics Wireless Zones.
 - 6) ‡ RF Expander Modules available in V5.1 or later only.