

**128k Memory Configurations. V7.4 - V7.8***Please read notes on p10.*

V7.4-V7.8 128k (1MBit)	Standard	Access	Enlarged	Apartments	Access 2	Special	Alarms	XDoor	IP Door
	00	01	02	03	04	05	06	07	08
Users	2000	1000	1000	500	1000	1000	1000	2000	4096
User Names	100	1000	100	500	1000	1000	100 (200)	100	10
User RF Fobs	25	25	0	25	25	25	25	25	0
Extra Door/DList for Users	0	0	0	0	0	0	0	2000	0
User Types	32	64	32	64	64	64	48	64	64
Card Only Users	0	0	0	0	0	0	0	0	5904
Areas	96	32	96	48	32	32	64	32	10
Doors	32	64	16	48	64	48	16	48	8
Lift Cars	3	6	3	4	6	4	3	4	0
Site Codes	6	5	6	6	5	6	5	6	8
TimeZones	32	32	32	32	32	32	32	32	16
Holidays	16	16	16	16	16	16	16	16	16
Diaries	10	10	10	10	10	10	10	10	5
Counters	8	8	16	4	4	8	8	8	0
Area Lists	96	32	96	48	32	32	64	32	64
Doors Lists	48	64	32	48	64	48	32	48	64
Siren Lists	32	16	32	16	16	8	32	8	1
Floor Lists	24	48	24	32	32	32	24	32	0
Lift Car Lists	6	12	6	6	6	8	6	8	0
Auxiliary Lists	32	32	32	16	32	32	32	32	4
Menu Groups	16	8	16	8	8	8	16	8	4
Access Groups	16	12	16	12	16	16	8	16	8
Process Groups	32	24	32	32	32	32	32	32	24
Interlock Groups	16	32	12	8	16	16	8	8	4
Comms Tasks	6	6	6	6	6	6	8	6	4
Phone Numbers	8	8	8	12	12	8	12	8	4
DTMF Controls	16	16	16	8	8	16	16	16	0
Function Zones	32	16	32	32	16	16	32	16	4
Calculated Auxes	32	16	32	32	16	16	32	16	4
Home Auxiliaries	48 (64)	32	64	32	32	32	64 (32)	32	0
Home Zones	32	16	64	16	16	16	64	16	0
Automation Auxiliaries	16	16	16	16	16	16	16	16	0
LCD Terminals	32	16	32	32	16	16	32	16	4
Touchscreen Terminals	2	2	2	0	2	2	2	0	0
Expander Modules 32Z	4	2	6	1 (2)	2	1	15	2	0
Expander Modules 16Z	6	6	8	2 (8)	4	2	0	2	0
Reader Modules	16	32	8	24 (32)	32	8	8	16	4
Mini Expander Modules	5	4	10	25 (5)	4	16	4	8	0
Analogue Modules	2	3 (4)	4	2	2	4	4	2	0
Intell. 4Dr Access Modules	0	0	2	4	0	8	2	8	0
LAN Pwr Supply Modules	2	2	2	6	4 (6)	2	2	2	0
Wireless Network Modules	0	0	6	0	0	0	0	0	0
RF Expander Modules	2	1	0	2	2	2	2	2	0
AirCon Control	0 (2)	0 (2)	4 (2)	0 (2)	0 (2)	0 (2)	4 (2)	0 (2)	0
Review Memory. *	1800 (2000)	1800 (2000)	1800 (2000)	1800 (2000)	1800 (2000)	1600 (2000)	2000	1800 (2000)	875 (1000)
EN Review: ^ Normal Mandatory	1300 500	1200 500	1300 500	1300 500	1200 500	1000 500	1500 500	1300 500	375 500

\* Applies only to Non EN firmware types. *See Note 7.*^ Applies only to EN firmware types. *See Note 7.*