

32k Memory Configurations. V7.4 - V7.8*Please read notes on p10.*

V7.4 - V7.8 32k (256kBit)	Standard	Access	Enlarged	Apartments	Access 2	Special	Alarm	XDoor
	00	01	02	03	04	05	06	07
Users	100	100	100	100	100	50	50	500
User Names	50	50	50	50 (100)	100	50	50	10
User RF Fobs	0	0	0	10	0	10	10	0
User Types	16	16	16	16	16	8	8	16
Card Only Users	0	0	0	0	0	0	0	0
Areas	24	16	8	16	16	16	16	8
Doors	4	8	16	4 (8)	8	4	4	20
Lift Cars	0	0	0	0	0	0	0	0
Site Codes	3	3	3	3	3	3	3	3
TimeZones	8	8	8	8	8	8	8	8
Holidays	8	8	8	8	8	8	8	8
Diaries	5	5	5	5	5	5	5	4
Counters	4	0	0	4	0	4	4	0
Area Lists	16	16	8	16	16	16	16	4
Doors Lists	8	16	16	8 (16)	16	8	8	16
Siren Lists	8	8	2	4	8	8	8	4
Floor Lists	0	0	0	0	0	0	0	0
Lift Car Lists	0	0	0	0	0	0	0	0
Auxiliary Lists	2	2	2	8	2	8	2	2
Menu Groups	8	8	8	8	8	8	8	8
Access Groups	8	8	8	8	8	8	8	8
Process Groups	24 (16)	24 (16)	24 (16)	24 (16)	24 (16)	24 (16)	24 (16)	24 (16)
Interlock Groups	0	0	0	0	0	0	0	0
Comms Tasks	5	5	5	5	5	5	5	4
Phone Numbers	6	6	6	6	6	6	6	6
DTMF Controls	8	4	4	4	4	8	4	4
Function Zones	32	16	16	16	16	32	32	16
Calculated Auxes	16	16	16	16	16	16	16	16
Home Auxiliaries	8	8	8	8	8	16	16	8
Home Zones	8	0	0	0	8	16	0	8
Automation Auxiliaries	0	0	0	0	0	0	0	0
LCD Terminals	8	8	8	8	8	8	8	4
Touchscreen Terminals	0	0	0	0	0	0	0	0
Expander Modules 32Z	1	1	0	0	1	1	2	0
Expander Modules 16Z	3	2	0	0 (2)	2	1	2	0
Reader Modules	2	4	2	2 (4)	4	2	2	10
Mini Expander Modules	1	0	2	8 (1)	0	3	0	0
Analogue Modules	0	0	1	0	0	0	0	0
Intelligent 4Dr Access Modules	0	0	2	0	0	0	0	0
Wireless Network Modules	0	0	0	0	0	0	0	0
RF Expander Modules	0	0	0	1	0	1	1	0
AirCon Control	0	0	0	0	0	0	0	0
Review Memory. *	300	550	500	400	400	300	300	400
EN Review: ^ Normal	150	300	150	150	150	150	100	150
Mandatory	250	250	250	250	250	250	250	250

* Applies only to Non EN firmware types. See Note 7.

^ Applies only to EN firmware types. See Note 7.